Presentation Checklist

- Laptop
- Speaker
- Radio
- Recorder
- Headset
- Splitter
- Candy
- Model Sat
- V71, 9700, D72
- Arrow, Elk
- Recordings
- Cheat Sheet
- Copies of presentation.
- AMSAT docs

FM SATELLITES THE WHERE-TO'S, HOW FOR'S AND WHAT-NOT'S

Ron Bondy, AD0DX <u>ad0dx@yahoo.com</u> For W0TLM Monday June 15, 2020 via Zoom

WHO MADE THESE SLIDES?

Paul Overn

KEOPBR: @KEOPBR

Recent Technician (November 2017), Upgraded to General in March 2018.

Mitch Ahrenstorff

AD0HJ

All around good guy and a great Ham. Extra @AD0HJ

Why satellites?

- Technician Limitation
- Repeaters are not very busy
- Challenge

WHAT CAN YOU DO ON THEM?

APRS SSTV / Pics CW Beacons Decode Beacons ISS Classroom Chats CW / SSB – (Linear) Sats FM Repeater - Sats



80 лет со дня рождения первого космонавта планеты Земля серия 2 - Ю.А.Гагарина 1/12

WHY SATELLITES?

Just like a land based repeater, except

Circling the globe at 17,000MPH Over 300 Miles Up 1,400 Miles away Low Transmit Power: 5 Watts to the sat. Low Power for Return: 250-500 MW back from the sat Frequency Changes – Doppler / polarization Transmit and Receive **Bands** are different


Maybe you can't do this, after all you are using a 5W transmitter, to make a 5200KM round trip, using a 2 pound box, approximately 4" square, in outer space, to repeat the signal to you, on a different band.

SATELLITES

LEO (Low Earth Orbit), FM repeaters

- SO-50
- AO-91
- AO-92
- PO-101 (Diwata-2 / Schedules)
- Lilacsat (Schedules)

More on the way!




A0-85

Each Sat is $1U: A "U" = 10CM \times 10CM \times 10CM = 3.97"$

FINDING SATELLITES

How to find them: Numerous software packages:

- IOS
 - GoSatWatch (\$10.00)
 - TrackSats (Free)
 - Satellite Tracker (\$10.00)
- PC Mac
 - SatPC32 (\$45.00 / \$80.00) <- Numerous other features
 - Orbitron
 - Predict
 - AMSAT Web Page
 - Mac Doppler <- More Features
- Android
 - Amsat Droid
 - Heavens Above
 - IIS Detector Pro
 - Look4Sat




FINDING THEM PART II GoSatWatch (iOS)

AO-85		11:34:33	3	11:53:34 AM 🔲		
Now		Passes	;	Û		
	Start	End	Peak	Mg		
Thurso	lay, Februa	ary 1, 2018				
~** <u>*</u>	SO-50 11:46:25 AM	11:57:24 AM	39° SW	4.5	>	
** <u>0</u>	AO-91 11:58:24 AM	12:06:43 PM	23° NE	4.3	>	
*	AO-85 1:28:07 PM	1:32:38 PM	7° N	5.0	>	
	AO-91 1:34:35 PM	1:43:18 PM	28° W	4.5	>	
*	AO-85 3:08:59 PM	3:17:13 PM	13° NE	4.6	>	
	LILACSAT 4:39:45 PM		26° E	3.3	>	
	AO-85 4:48:52 PM	5:00:45 PM	44° NE	3.4	>	
* 2	LILACSAT 6:13:58 PM		25° W	5.1	>	
	AO-85 6:29:24 PM	6:40:54 PM	33° SW	5.1	>	
*	AO-92 8:42:17 PM	8:51:04 PM	37° E		>	
*** <u>2</u>	AO-92 10:16:49 PM	10:24:15 PM	17° W		>	
Friday,	February 2	2, 2018				
World	(sky	Passes	Sate	llites Se	ttings	

AO-85	11:32:18	11:55:49 AM 🔲		
Passes	AO-85	Ê		
		\times		
		$\wedge \lambda$		
		\times V		
⊥ 5° NW		± 5° SE		
4:48:52 PN	4:54:38 PM	5:00:45 PM		
) 🕘			
World Sky	Passes	Satellites Settings		

FINDING THEM PART III GoSatWatch (iOS)



FREQUENCIES

There are two issues with frequencies that we have to find solutions too:

- RX and TX are on different bands
- Doppler Shift

Bands:

SO-50:

- V/u
- Up = VHF
- Down = UHF
- Uplink Tone = 67 (74 for initialization)

Others:

- U/v
- See Frequency Chart
- Uplink Tone = 67

What's the solution: Full Duplex Radios!! Being able to hear yourself is a huge advantage!

DOPPLER

As the satellite travels across the sky, the frequency changes. Think of how a train whistle pitch changes as it gets closer and then goes away.

Although both UHF and VHF are affected, it is safe to only adjust the UHF frequency


On AO-92 UHF is Up. VHF is Down.

- AO-92 for you to transmit, you adjust the uplink freq,

We adjust for Doppler in 5khz increments. Start 10 khz above (or below) the listed frequency and work to 10 khz below (or above) the listed frequency. Sat frequencies are listed "At the Sat". The frequency of the bird doesn't change. The frequency changes on the way to the sat.

*Start below if RX, start above if TX

DOPPLER



FREQUENCIES

	SO-50	67 Hz			AO-91		67 Hz			
	Preset #3	Up (FM)	Down (FM)		Preset #2	Up (FM)	Down (FM)			
	AOS		436.805		AOS	435.240				
	2		436.800		2	435.245				
	Mid	145.850	436.795		Mid	435.250	145.960			
	4		436.790		4	435.255				
	LOS		436.785		LOS	435.260			L-Band	AO-92
									AOS	1267.320
										1267.325
	LilacSat-2	No tone			AO-92		67 Hz			1267.330
		Up (FM)	Down (FM)		Preset #1	Up (FM)	Down (FM)			1267.335
	AOS		437.210		AOS	435.340				1267.340
	2		437.205		2	435.345				1267.345
	Mid	144.350	437.200		Mid	435.350	145.880		TCA	1267.350
	4		437.195		4	435.355		,		1267.355
	LOS		437.190		LOS	435.360				1267.360
										1267.365
		<- Doppler is High to Low		w	PO-101		141.3			1267.370
					10-101	Up (FM)	Down (FM)			1267.375
					AOS	437.490	Down (nw)		LOS	1267.380
					2	437.495				
					Mid	437.500	145.900			
					4	437.505	140.000			
					LOS	437.505				
			@Diwata2		tter					
	Workata2 From Witter									

POLARIZATION

The sats are tumbling through space. As they "roll" you need to turn the antennae compensating for the change it orientation. This is called the "Wrist Twist"

Satellites have personality: AO-91 is a dance – Tumbles AO-92 Easiest – Easy to get into the repeater, not much of a tumble, but busy. SO-50 Easy, stable, but not many people.

SQUELCH

The satellites do not have enough power to open the squelch, you need to open it manually.



Build your rig for reception.

EQUIPMENT Build your setup for the best <u>RECEIVE</u> system you can.

Antennae:

- Elk or Arrow: \$100-\$200 (Homemade Tape Measure Antennae)
- Some stationary for the shack, but seem to be home made
- Whip antennae
- Homemade stationary with elevator and azimuth rotators.

Radio UHF / VHF:

- Must be full duplex or two radios. Split does not allow you to hear yourself.
 - HT: Kenwood TH-D72a (APRS Built in)
 - Mobile: Kenwood TM-V71A
 - Mobile: Kenwood TM-D710
 - Yaesu 1634: This is really 2 x 817s
 - 2 Beufungs
 - SDR for receive and single radio to transmit.
 - ICOM 910H or 9700.



Recorder:

- Used to record a pass
 - Must have a "Line In"
 - Some radios have a record function. But most pass recordings are 10-12 minutes long.
 - Best to record off the headphone jack, not just hanging off your neck.

Headset:

- Need to prevent feedback. This is for full duplex ops

Optional:

- Phone or PC showing where the sat is.
- Compass Can use the one on your phone

SO-50 w/HT

More stuff:

Headsets

Compass

Splitter + digital recorder (logging)

More hands?

HOW TO START

Determine when and where a sat will be: *Starting in the north, moving to South East, with 45 degrees in the middle.*

Get your radio ready: *Preprogram the frequencies, tones, etc. Set it up for the start.*

Turn on your recorder. This is going to happen fast. Hams will talk very fast.

Hook up your antennae. Seriously. I have forgotten this.

When the sat is at 5 degrees, point the antennae where the satellite will appear. You can work lower passes when you get more comfortable.

Listen for quite

Listen. Listen. Listen

Find a call and call them: *AD0HJ* this is *KE0PBR* at *EN34*. Then enjoy the fun.



How does it go

Ways to start:

- Listen for an active person then call them
 - WY7AA KE0PBR EN26

Next is a reply, from WY7AA

KE0PBR WY7AA DN71

Comes your reply:

• WY7AA QSL,73

And their reply

• QSL, 73

Or if you are available, you can throw your call out.

KE0PBR EN26 <- Do this Rarely, just call someone

Very similar to a HF Contest QSO.

QSO – DON'TS

Keep in mind on the FM sats, the pass is 8-10 minutes long (each orbit is 90 minutes long) and only one person can use the repeater at a time. This means keep the amount of time your talking low.

- Do not call CQ or Whistle
- Do not rag chew (unless only 2-3 people are on the bird). This can happen on northern (Polar Bear) passes.
- Limit conversation of bare minimum. Calls, grids, salutation.
- Do not blind call your call sign excessively.

On FM sats, do not call CQ – No Rag chews either.

PLAY RECORDING





Many ops chase grid squares. Get out of your shack and go activate them!!! Use Twitter to announce when you are roving.

People are very appreciative of "Rovers"

HELPFUL APPS




True Heading

Diaptra - Android



HELPFUL APPS

Maidenhead



AWARDS

Rover Award: Activate a number of grid squares away from your QTH.

Satellite Communication Award: Just have a QSO on a bird.

Oscar Satellite Communications Achievement Award: Have 20 confirmed QSOs

Oscar Sexagesimal Award: Have 60 confirmed QSOs

Oscar Century Award: Have 100 confirmed QSOs

W4AMI Satellite Achievement Award: Have 1000 confirmed QSOs

488: have a confirmed QSO with someone from each of the 488 grids in the continental USA.

VHF/UHF Century award, SATPX (50 different prefixes worked), WAS, WAC, DXCC....



The Big one on sats:

Started on Twitter and is called #WMPLOTA "Walmart Parking Lot on the Air"

WMPLOTA.ORG

Rules are simple:

Walmart Parking Lots on the Air is in July. To participate in this scheme you do not need to register in advance or pay any dues. You simply need to operate an amateur radio satellite station, and then choose to be an WMPLOTA Employee (activator), who operates portable from any Walmart parking lot, or a Shopper (chaser) operating from another location and contacting Employees. When making amateur radio contacts, it is common practice to exchange your callsign and grid square during the contact. WMPLOTA Employees are encouraged to announce /wm and also exchange the Walmart Store Number during the contact, which will be used by anyone participating in the awards scheme. The Walmart Store Number can be found on the store receipt or through the <u>Walmart Store</u> Finder online.

Employees, please take a picture of your operating location, including a branded shopping cart or a recognizable portion of a Walmart (or Sam's Club) branded store. Selfies are encouraged, and extra points will be awarded for any operating picture that includes a Walmart greeter or security staff member. Big points and notoriety is yours if you operate shopping cart mobile /wm/m/p, but be careful and wear a high-vis vest!

HAMBADGES






#WMPLOTA STORE MANAGER









RESOURCES

AMSAT: Bulletin Board AMSAT: ANS (Amsat News Service)

You Tube – Space Comms Twitter (KOFFY, WD9EWK, AMSAT, KE0PBR, N9EAT, AD0JH, KE4AL, The_grid_life, GridmasterHeat etc) Facebook (AMSAT Page)

Amsat.ORG Amsay-UK.com Work-sat.com <- Dated

DMR Talkgroup 98006 (AMSAT Twitter net at 9:00pm CST Wednesdays)

KE0PBR.Wordpress.com

MY MISTAKES

Transmit on the receive frequency Didn't start recorder Didn't hook up antennas Didn't program the tone / Turn on the tone Started in the south, with the sat at the north Choose wrong satellites frequencies Forgot who I was calling Forgot my Grid Square Stomped on people (low power, and I bump them from repeater) Interrupted QSO Plugged recorder into the Transmit side of the radio. Didn't start recorder Didn't Open Squelch Did 50khz steps instead of 5khz steps for Doppler

